



ENERGY 1000 START 230-400V



Обзор

ENERGY 1000 START 230-400V

cod. 829008

Battery charger and starter for charging free electrolyte batteries (WET) with 12/24V voltage and starting all kinds of cars, vans, light trucks, earth moving equipment, tractors and trucks.

Features:

- choice of normal charge, quick charge (BOOST), quick start
- timer for quick charge
- remote control
- display of charging and starting current
- protection against overloads and polarity reversal.



3 PH 230V-400V



МАРКИРОВКА CE



СЕРТИФИКАЦИИ EAC



ДИСТАНЦИОННОГО УПРАВЛЕНИЯ

Технические данные

CODE	КОД 829008	A_{EFF}	ТОК ЭФФЕКТИВНОГО ЗАРЯДА 100 А		РЕГУЛИРОВКА ПОЗИЦИИ 5
V_{3PH}	ТРЕХФАЗНЫЙ НАПРЯЖЕНИЕ СЕТИ 230 / 400 V	A_{EN}	ТОК КОНВЕНЦИОНАЛЬНОГО ЗАРЯДА EN60335-2-29 80 А		РАЗМЕРЫ 38 x 56 x 88,5 cm
F	ЧАСТОТЫ СЕТИ 50 / 60 Hz	A_{1V/C}	ТОК ЗАПУСКА 1V / C EN60335-2-29 640 А		ВЕС 45 kg
P_{CHARGE}	МОЩНОСТЬ ЗАРЯДА 2,5 KW	A_{START MAX}	МАКСИМАЛЬНЫЙ ТОК ПУСКА 1000 А		КОД EAN 800489736539 8



ENERGY 1000 START 230-400V



МОЩНОСТЬ ЗАПУСКА 20 KW



МИН. НОМИНАЛЬНАЯ ССЫЛКА
ПОТЕНЦИАЛ 20 А



ЧАСТЕЙ / ПАЛЛЕТ 6 pz/pallet



НАПРЯЖЕНИЕ ЗАРЯДКИ 12 / 24 V



МАКС. НОМИНАЛЬНАЯ ССЫЛКА
ПОТЕНЦИАЛ 1200 / 800 А



ЧАСТЕЙ / ПАЛЛЕТ - В 4 pz/pallet-B

Входящие в комплект аксессуары

null - 123456

null - 712025

null - 123467

null - 712026

null - 123993