



## LEADER 400 START 230V 12-24V



### Обзор

#### LEADER 400 START 230V 12-24V

cod. 807551

Battery charger and starter for charging free electrolyte batteries (WET) with 12/24V voltage, and starting all types of petrol-driven and diesel-driven vehicles, up to 70 hp.

#### Features:

- choice of normal charge, quick charge (BOOST), quick start
- display of charging and starting current
- protection against overloads and polarity reversal.



1 PH 230V



МАРКИРОВКА CE



СЕРТИФИКАЦИИ EAC

### Технические данные

<b>CODE</b>	КОД 807551	<b>A<sub>EFF</sub></b>	ТОК ЭФФЕКТИВНОГО ЗАРЯДА 45 А		РЕГУЛИРОВКА ПОЗИЦИИ 3
<b>V<sub>1PH</sub></b>	ОДНОФАЗНОЕ НАПРЯЖЕНИЕ СЕТИ 230 V	<b>A<sub>EN</sub></b>	ТОК КОНВЕНЦИОНАЛЬНОГО ЗАРЯДА EN60335-2-29 30 А		РАЗМЕРЫ 26,5 x 34,5 x 23 cm
<b>F</b>	ЧАСТОТЫ СЕТИ 50 / 60 Hz	<b>A<sub>1V/C</sub></b>	ТОК ЗАПУСКА 1V / C EN60335-2-29 180 А		ВЕС 10,9 kg
<b>P<sub>CHARGE</sub></b>	МОЩНОСТЬ ЗАРЯДА 1 KW	<b>A<sub>START MAX</sub></b>	МАКСИМАЛЬНЫЙ ТОК ПУСКА 300 А		КОД EAN 800489764804 0
<b>P<sub>START</sub></b>	МОЩНОСТЬ ЗАПУСКА 6,4 KW	<b>C<sub>MIN</sub></b>	МИН. НОМИНАЛЬНАЯ ССЫЛКА ПОТЕНЦИАЛ 20 А		ЧАСТЕЙ / ПАЛЛЕТ 27 pz/pallet
	НАПРЯЖЕНИЕ ЗАРЯДКИ 12 / 24 V	<b>C<sub>MAX</sub></b>	МАКС. НОМИНАЛЬНАЯ ССЫЛКА ПОТЕНЦИАЛ 700 А		ЧАСТЕЙ / ПАЛЛЕТ - В 36 pz/pallet-B

### Входящие в комплект аксессуары

Telwin SPA | Via della Tecnica 3 - 36030 VILLAVERLA (VI) ITALY - Tel. +39-0445-858811 - Fax +39-0445-858800/801 - www.telwin.com  
01.09.2020



## LEADER 400 START 230V 12-24V

null - 123425



null - 712002



null - 712001