



ENERGY 1500 START 230-400



Обзор

ENERGY 1500 START 230-400

cod. 829009

Battery charger and starter for charging free electrolyte batteries (WET) with 12/24V voltage and starting all kinds of cars, vans, light trucks, earth moving equipment, tractors and trucks.

Features:

- choice of normal charge, quick charge (BOOST), quick start
- timer for quick charge
- remote control
- display of charging and starting current
- protection against overloads and polarity reversal.



3 PH 230В-400В



МАРКИРОВКА CE



СЕРТИФИКАЦИИ EAC



ДИСТАНЦИОННОГО УПРАВЛЕНИЯ

Технические данные

CODE	КОД 829009	A_{EFF}	ТОК ЭФФЕКТИВНОГО ЗАРЯДА 150 / 250 А		РЕГУЛИРОВКА ПОЗИЦИИ 6
V_{3PH}	ТРЕХФАЗНЫЙ НАПРЯЖЕНИЕ СЕТИ 230 / 400 V	A_{EN}	ТОК КОНВЕНЦИОНАЛЬНОГО ЗАРЯДА EN60335-2-29 130 / 220 А		РАЗМЕРЫ 38 x 56 x 88,5 cm
F	ЧАСТОТЫ СЕТИ 50 / 60 Hz	A_{1V/C}	ТОК ЗАПУСКА 1V / С EN60335-2-29 1000 / 1300 А		ВЕС 69 kg
P_{CHARGE}	МОЩНОСТЬ ЗАРЯДА 7 KW	A_{START MAX}	МАКСИМАЛЬНЫЙ ТОК ПУСКА 1700 / 2000 А		КОД EAN 800489736540 4



ENERGY 1500 START 230-400



МОЩНОСТЬ ЗАПУСКА 44 KW



МИН. НОМИНАЛЬНАЯ ССЫЛКА
ПОТЕНЦИАЛ 70 А



ЧАСТЕЙ / ПАЛЛЕТ 4 pz/pallet



НАПРЯЖЕНИЕ ЗАРЯДКИ 12 / 24 V



МАКС. НОМИНАЛЬНАЯ ССЫЛКА
ПОТЕНЦИАЛ 2000 / 4000 А



ЧАСТЕЙ / ПАЛЛЕТ - В 6 pz/pallet-B

Входящие в комплект аксессуары

null - 123993

null - 713260

null - 713162