



DYNAMIC 620 START 230V 12-24V



Обзор

DYNAMIC 620 START 230V 12-24V

cod. 829384

Battery charger and starter for charging free electrolyte batteries (WET) with 12/24V voltage and starting all kinds of cars, vans and light trucks.

Features:

- choice of normal charge, quick charge (BOOST), quick start
- timer for quick charge
- display of charging and starting current
- protection against overloads and polarity reversal.



1 PH 230V



МАРКИРОВКА CE



СЕРТИФИКАЦИИ EAC

Технические данные

CODE	КОД 829384	A_{EFF}	ТОК ЭФФЕКТИВНОГО ЗАРЯДА 90 А		РЕГУЛИРОВКА ПОЗИЦИИ 4
V_{1PH}	ОДНОФАЗНОЕ НАПРЯЖЕНИЕ СЕТИ 230 V	A_{EN}	ТОК КОНВЕНЦИОНАЛЬНОГО ЗАРЯДА EN60335-2-29 70 А		РАЗМЕРЫ 36,5 x 46 x 75,5 cm
F	ЧАСТОТЫ СЕТИ 50 / 60 Hz	A_{1V/C}	ТОК ЗАПУСКА 1V / C EN60335-2-29 360 А		ВЕС 24 kg
P_{CHARGE}	МОЩНОСТЬ ЗАРЯДА 2 KW	A_{START MAX}	МАКСИМАЛЬНЫЙ ТОК ПУСКА 570 А		КОД EAN 800489773286 2
P_{START}	МОЩНОСТЬ ЗАПУСКА 10 KW	C_{MIN}	МИН. НОМИНАЛЬНАЯ ССЫЛКА ПОТЕНЦИАЛ 20 А		ЧАСТЕЙ / ПАЛЛЕТ 9 pz/pallet
	НАПРЯЖЕНИЕ ЗАРЯДКИ 12 / 24 V	C_{MAX}	МАКС. НОМИНАЛЬНАЯ ССЫЛКА ПОТЕНЦИАЛ 1550 А		ЧАСТЕЙ / ПАЛЛЕТ - B 6 pz/pallet-B